







unimec legends

All standard legends are white on black caps.
The size of the legends listed may not correspond to the actual size.
Please ask your local distributor, if you do not find what you need on the list. New legends may have been added after this catalogue was printed.
Custom legends and other colour combinations are available, please contact your local distributor.

Standard Keycap Legends

PART NO.			PART NO.			PART NO.		
LEGEND	 18__	 18__	LEGEND	 18__	 18__	LEGEND	 18__	 18__
0	000	200	A	010	210	=	060	260
1	001	201	B	011	211	%	058	258
2	002	202	C	012	212	:	055	255
3	003	203	D	013	213)	062	262
4	004	204	E	014	214	ON/OFF	017	217
5	005	205	F	015	215	STOP	018	218
6	006	206	G	063	263	START	031	231
7	007	207	H	064	264	FEED	032	232
8	008	208	I	065	265	REPEAT	035	235
9	009	209	J	066	266	CLEAR	036	236
10	020	220	K	067	267	LOAD	037	237
11	021	221	L	068	268	RESET	038	238
12	022	222	M	069	269	RUN	039	239
13	023	223	N	070	270	PRINT	040	240
14	024	224	O	071	271	CR	043	243
15	025	225	P	072	272	MANUAL	044	244
16	026	226	Q	073	273	HOLD	045	245
17	027	227	R	074	274	BYPASS	046	246
18	028	228	S	075	275	END	047	247
19	029	229	T	076	276	CANCEL	048	248
20	030	230	U	077	277	SUB.	049	249
21	083	283	V	078	278	CTRL.	050	250
22	084	284	W	079	279	ESC.	051	251
23	085	285	Z	080	280	CRE.	052	252
24	086	286	X	081	281	DSP.	053	253
25	087	287	Y	082	282	ENTER	105	305
26	088	288	#	107	307	SHIFT	106	306
27	089	289	*	019	219	ON	116	316
28	090	290	□	016	216	OFF	117	317
29	091	291	→	033	233			
30	092	292	←	133	333			
31	093	293	↑	034	234			
32	094	294	↓	134	334			
33	095	295	↶	135	335			
34	096	296	↷	115	315			
35	097	297	↔	041	241			
36	098	298	><	061	261			
37	099	299	+	054	254			
38	100	300	-	059	259			
39	101	301	•	056	256			
40	102	302	+	057	257			